

A PSEUDOSPECTRAL ANALOGUE OF DISCRETE BORG-TYPE THEOREMS

V. B. KIRAN KUMAR¹, G. KRISHNA KUMAR²

ABSTRACT. The pseudospectral versions of the discrete Borg-type theorems are obtained in this article using some simple linear algebraic techniques. In particular, we prove that the periodic potential of a discrete Schrödinger operator is almost a constant if and only if the pseudospectrum of the operator is connected. This result is further extended to more general settings and the connection to the well-known Ten Martini problem is also established. The numerical illustrations done at the end will justify the results developed.

1. INTRODUCTION

Borg's theorem is a classical result in inverse spectral theory that has connections with several problems in quantum mechanics. In 1946, G. Borg proved that the periodic potential of a Schrödinger operator is constant almost everywhere if and only if the essential spectrum of the operator is connected (see [2]). For mathematicians, this is an interesting result since it determines the nature of the potential from the given spectral data of the operator. This result is used as an important tool for various problems in several other branches of science, for example, computing the density of a guitar string from its frequency data, to determine the shape of a drum etc. (see [7]). The discrete versions of Borg's theorem were also considered by several mathematicians. In 1975, H. Flaschka discovered the discrete Borg's theorem (see [4]). There were several modifications and generalizations of this result, which we refer as Borg-type theorems. In [5], the authors gave a pure linear algebraic approach to prove the discrete Borg's theorem. The techniques developed in [5] were used to obtain discrete Borg-type theorems in [8].

There are several notions which generalize spectrum of an operator and each of them are important for necessary reasons. Pseudospectrum is one of the important generalizations of spectrum. For $\epsilon > 0$ the ϵ -pseudospectrum of an operator A is denoted by $\Lambda_\epsilon(A)$ and defined as

$$\Lambda_\epsilon(A) := \{z \in \mathbb{C} : zI - A \text{ is not invertible or } \|(zI - A)^{-1}\| \geq \epsilon^{-1}\}.$$

Date: Received: xxxxxx; Revised: yyyyyy; Accepted: zzzzzz.

¹ Corresponding author.

2010 *Mathematics Subject Classification.* Primary 47B35; Secondary 47B36.

Key words and phrases. Spectrum; Pseudo Spectrum; Borg-type Theorems.

Here I denotes the identity operator. For information on the importance and applications of pseudospectrum, refer to [11]. In this article, we establish the pseudospectral version of the discrete Borg-type theorems. We prove that *the pseudospectrum of the discrete Schrödinger operator is connected if and only if the periodic potential is almost a constant*. This result is further extended to general Jacobi operators and block Laurent operators. Finally, we connect the results developed with the well-known Ten Martini problem (see [1]).

Consider the Schrödinger operator $\tilde{A}$ on a suitable subspace of $L^2(\mathbb{R})$ defined by

$$(1.1) \quad \tilde{A}u = -\ddot{u} + v \cdot u,$$

where v is an essentially bounded periodic potential. This is an important unbounded operator that arises widely in quantum mechanics. The information of spectrum of this operator is valuable for understanding many physical phenomena in quantum mechanics. There are several classical results which reveals the connection between the nature of spectrum of $\tilde{A}$ and the potential function v . The celebrated Borg's theorem states that there are no gaps in the essential spectrum of $\tilde{A}$ if and only if the periodic potential function v reduces to a constant almost everywhere [2].

1.1. Discrete Schrödinger operator. The simple finite difference approximation will reduce the Schrödinger operator defined in (1.1), to a bounded self-adjoint operator on $\ell^2(\mathbb{Z})$, which we call as the discrete Schrödinger operator. The discrete version of Borg's theorem was proved using simple linear algebraic techniques in [5]. The key idea used in [5] is the identification of the discrete Schrödinger operator as a block Laurent operator (after some scaling and translation). This identification helps us to use the rich theory of spectral analysis of block Laurent operators to the problem. Here we explain this identification briefly.

Consider the Schrödinger operator with periodic potential v and without loss of generality assume that the periodicity of v is 1. Now approximate the equation (1.1) in the interval $[-n, n]$ with $n \in \mathbb{N} \cup \{\infty\}$ by using p equispaced points in each interval $[j, j+1] \subset [-n, n]$. By using the standard difference we have

$$-u''(x_{i,(j)}) = \frac{-u(x_{i+1,(j)}) + 2u(x_{i,(j)}) - u(x_{i-1,(j)})}{h^2}$$

with $h = 1/p$. For $j = -n, \dots, n-1$ we have $x_{s,(j)} = j + sh$ where $s = 0, \dots, p-1$. Letting $n = \infty$, this can be treated as an operator denoted by $\tilde{A}$ acting on the sequence space $\ell^2(\mathbb{Z})$

and is defined by

$$\tilde{A}(\{u_n\}_{n \in \mathbb{Z}}) = \frac{-(u_{n-1} + u_{n+1}) + 2u_n}{h^2} + v_n u_n; \{u_n\}_{n \in \mathbb{Z}} \in \ell^2(\mathbb{Z}),$$

where the sequence $\{v_n\}_{n \in \mathbb{Z}}$ is obtained as the values of the periodic function v at p equispaced points in an interval of length 1. The periodicity of v will imply that the sequence $\{v_n\}_{n \in \mathbb{Z}}$ is also periodic with period p . The matrix representation of $\tilde{A}$ with respect to the standard basis of $\ell^2(\mathbb{Z})$ is obtained as a tridiagonal matrix (up to the scaling factor h^2) as

$$\tilde{A} = \begin{bmatrix} \ddots & \ddots & & & & & \\ \ddots & \ddots & & \ddots & & & \\ & -1 & 2 + h^2 v(x_{0,(1)}) & -1 & & & \\ & & \ddots & \ddots & \ddots & & \\ & & & -1 & 2 + h^2 v(x_{p-1,(1)}) & -1 & \\ & & & & -1 & 2 + h^2 v(x_{0,(2)}) & -1 \\ & & & & & \ddots & \ddots & \ddots \\ & & & & & & \ddots & \ddots \end{bmatrix}.$$

Since v is periodic, we have $v(x_{s,(j)}) = v(x_{s,(j+1)})$ for all $s = 0, \dots, p-1$. Thus the sequence appearing in the main diagonal becomes periodic with period p . When n is finite, the resulting matrix of size np is the truncation of the bi-infinite matrix reported above. When $n = \infty$, up to some scaling and translation by a scalar multiple of the identity operator, this operator can be identified as the block Laurent operator defined by

$$(1.2) \quad A := \begin{bmatrix} \cdot & \cdot & \cdot & \cdot & \cdots & \cdot & \cdot \\ \cdot & A_1 & A_0 & A_{-1} & \cdots & \cdot & \cdot \\ \cdot & \cdot & A_1 & A_0 & A_{-1} & \cdot & \cdot \\ \cdot & \cdot & \cdot & A_1 & A_0 & A_{-1} & \cdot \\ \cdot & \cdot & \cdots & \cdots & \cdot & \cdot & \cdot \end{bmatrix}$$

where

$$A_1 = \begin{bmatrix} 0 & 0 & \cdots & 1 \\ 0 & 0 & \cdots & 0 \\ \cdot & \cdot & \cdots & \cdot \\ 0 & 0 & \cdots & 0 \end{bmatrix}, \quad A_{-1} = \begin{bmatrix} 0 & 0 & \cdots & 0 \\ 0 & 0 & \cdots & 0 \\ \cdot & \cdot & \cdots & \cdot \\ 1 & 0 & \cdots & 0 \end{bmatrix} \quad \text{and} \quad A_0 = \begin{bmatrix} v_1 & 1 & \cdots & 0 \\ 1 & v_2 & \cdots & 0 \\ \cdot & \cdot & \cdots & \cdot \\ 0 & 0 & \cdots & v_p \end{bmatrix}.$$

Thus after some suitable translation and scaling the discrete Schrödinger operator $\tilde{A}$ becomes the operator A defined in (1.2). It is worthwhile to notice that (1.2) gives the matrix representation of the bounded self-adjoint operator $A : \ell^2(\mathbb{Z}) \rightarrow \ell^2(\mathbb{Z})$ defined by

$$(1.3) \quad A(x_n) = (x_{n-1} + x_{n+1} + v_n x_n)$$

with respect to the standard orthonormal basis.

Let f be the matrix valued symbol of the Laurent operator A , obtained from the matrix representation (1.2) by $f(\theta) = A_0 + A_{-1}e^{-i\theta} + A_1e^{i\theta}$, $-\pi < \theta \leq \pi$. Then we have for $-\pi < \theta \leq \pi$,

$$f(\theta) = \begin{bmatrix} v_1 & 1 & 0 & \cdots & e^{i\theta} \\ 1 & v_2 & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ e^{-i\theta} & \cdot & \cdot & \cdots & v_p \end{bmatrix}.$$

Let $\sigma(A)$ and $\Lambda_\epsilon(A)$ denote the spectrum and ϵ -pseudospectrum of A respectively (for $\epsilon > 0$). Then we have the following identities for $\sigma(A)$ and $\Lambda_\epsilon(A)$ (see for eg. [10]).

$$(1.4) \quad \sigma(A) = \sigma(f) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f(\theta)) \text{ and } \Lambda_\epsilon(A) = \Lambda_\epsilon(f) = \bigcup_{-\pi < \theta \leq \pi} \Lambda_\epsilon(f(\theta)).$$

Also since $f(\theta)$ is a $p \times p$ Hermitian matrix for each $-\pi < \theta \leq \pi$, we have from [11], $\Lambda_\epsilon(f(\theta)) = \sigma(f(\theta)) + \Delta_\epsilon$, where $\Delta_\epsilon := \{z \in \mathbb{C} : |z| \leq \epsilon\}$ and

$$\sigma(f(\theta)) + \Delta_\epsilon := \{z : z = z_1 + z_2, z_1 \in \sigma(f(\theta)), z_2 \in \Delta_\epsilon\},$$

which is equal to $\{z : \text{dist}(z, \sigma(f(\theta))) \leq \epsilon\}$. It is worthwhile to notice that the symbol f can be chosen to be any member of the set $\{f_k; k = 0, 1, 2 \dots p-1\}$, where f_k is defined by

$$f_k(\theta) = \begin{bmatrix} v_{k+1} & 1 & 0 & \cdots & e^{i\theta} \\ 1 & v_{k+2} & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ e^{-i\theta} & \cdot & \cdot & \cdots & v_{k+p} \end{bmatrix}, \quad k = 0, 1, \dots, p-1.$$

Because of the periodicity of the sequence $\{v_n\}_{n \in \mathbb{Z}}$, we have the freedom to choose any one of the f'_k s. These identities will play an important role in the proof of the main results of this article.

2. PSEUDO BORG-TYPE THEOREMS

In this section we prove the pseudospectral versions of discrete Borg's theorem. We prove that the pseudospectrum of the discrete Schrödinger operator with periodic potential is connected whenever the potential is almost a constant.

Theorem 2.1. *Let A be the discrete Schrödinger operator with periodic potential sequence $\{v_n\}_{n \in \mathbb{Z}}$ defined in (1.3) and assume that the ϵ -pseudospectrum of A , $\Lambda_\epsilon(A)$ is connected for some $\epsilon > 0$. Then there exists a constant c such that $\sup_{n \in \mathbb{Z}} |v_n - c| \leq 2\epsilon(p-1)$, where p is the period of the potential sequence v_n .*

Proof. Consider the symbols f_k of A defined by

$$f_k(\theta) = \begin{bmatrix} v_{k+1} & 1 & 0 & \cdots & e^{i\theta} \\ 1 & v_{k+2} & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ e^{-i\theta} & \cdot & \cdot & \cdots & v_{k+p} \end{bmatrix}, \quad k = 0, 1, \dots, p-1.$$

Let $\sigma(f_k(\theta)) = \{\lambda_1(f_k(\theta)) \geq \lambda_2(f_k(\theta)) \geq \cdots \geq \lambda_p(f_k(\theta))\}$ for each $-\pi < \theta \leq \pi$. Now we consider the sub matrices J_k and J_{k+1} of $f_k(\theta)$ defined by

$$J_k := \begin{bmatrix} v_{k+1} & 1 & 0 & \cdots & 0 \\ 1 & v_{k+2} & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ 0 & 0 & 0 & \cdots & v_{k+p-1} \end{bmatrix}, \quad J_{k+1} := \begin{bmatrix} v_{k+2} & 1 & 0 & \cdots & 0 \\ 1 & v_{k+3} & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ 0 & 0 & 0 & \cdots & v_{k+p} \end{bmatrix}.$$

It is true that J_k and J_{k+1} are Jacobi matrices. Let

$$\sigma(J_k) = \{\mu_{1,k} \geq \mu_{2,k} \geq \cdots \geq \mu_{p-1,k}\}, \quad \sigma(J_{k+1}) = \{\mu_{1,k+1} \geq \mu_{2,k+1} \geq \cdots \geq \mu_{p-1,k+1}\}.$$

The Cauchy interlacing properties for eigenvalues of Hermitian matrices gives

$$\lambda_1(f_k(\theta)) \geq \mu_{1,k} \geq \lambda_2(f_k(\theta)) \geq \cdots \geq \lambda_{p-1}(f_k(\theta)) \geq \mu_{p-1,k} \geq \lambda_p(f_k(\theta)),$$

$$\lambda_1(f_k(\theta)) \geq \mu_{1,k+1} \geq \lambda_2(f_k(\theta)) \geq \cdots \geq \lambda_{p-1}(f_k(\theta)) \geq \mu_{p-1,k+1} \geq \lambda_p(f_k(\theta)).$$

The above inequalities are true for all $-\pi < \theta \leq \pi$. Since $\Lambda_\epsilon(A)$ is connected and

$$\Lambda_\epsilon(A) = \bigcup_{-\pi < \theta \leq \pi} \Lambda_\epsilon(f_k(\theta)) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f_k(\theta)) + \Delta_\epsilon,$$

we have $\bigcup_{-\pi < \theta \leq \pi} \Lambda_\epsilon(f_k(\theta))$ is connected for all $k = 0, \dots, p-1$. Therefore we have

$$|\lambda_{j,k}^- - \lambda_{j+1,k}^+| \leq 2\epsilon \text{ for each } k = 0, 1, \dots, p-1 \text{ and } j = 1, 2, \dots, p,$$

where $\lambda_{j,k}^+ := \max_\theta \lambda_j(f_k(\theta))$ and $\lambda_{j,k}^- := \min_\theta \lambda_j(f_k(\theta))$. We claim that $|\mu_{j,k'} - \mu_{j,k''}| \leq 2\epsilon$ for all $j = 1, 2, \dots, p$ and for any two different k', k'' . If this is not the case, then we have some k', k'' and j such that $|\mu_{j,k'} - \mu_{j,k''}| > 2\epsilon$. From the interlacing property mentioned above and from the fact that we can choose any of the symbol f_k , we get the contradiction to the fact that the ϵ -pseudospectrum of A is connected. Thus the j^{th} eigenvalue of $J_{k'}$ and $J_{k''}$ are atmost separated by 2ϵ distance. Consider $k' = 0$ and $k'' = 1$, we have

$$|\text{Trace}(J_0) - \text{Trace}(J_1)| \leq 2\epsilon(p-1).$$

Therefore we get

$$\left| \sum_{j=1}^{p-1} v_j - \sum_{j=2}^p v_j \right| \leq 2\epsilon(p-1).$$

Thus $|v_1 - v_p| \leq 2\epsilon(p-1)$. In general by considering J_0 and J_{i-1} we get

$$\left| \sum_{j=1}^{p-1} v_j - \sum_{j=i}^{p-2+i} v_j \right| = |\text{Trace}(J_0) - \text{Trace}(J_{i-1})| \leq 2\epsilon(p-1),$$

and therefore $|v_{i-1} - v_p| \leq 2\epsilon(p-1)$ for all $i = 2, 3, \dots, p$. Hence by choosing $c = v_p$ we get the desired result. $\square$

The following theorem gives the converse of the above result.

Theorem 2.2. *Let A be the discrete Schrödinger operator with periodic potential sequence $\{v_n\}_{n \in \mathbb{Z}}$ defined by (1.3). If there exists a constant c such that $\sup_{n \in \mathbb{Z}} |v_n - c| \leq \epsilon$ for some $\epsilon > 0$, then $\Lambda_{2\epsilon}(A)$ is connected.*

Proof. Since there exists a constant c such that $\sup_{n \in \mathbb{N}} |v_n - c| \leq \epsilon$, we have $|v_i - v_j| \leq 2\epsilon$, for every i, j . Thus the matrix valued symbol $f(\theta)$ becomes

$$f(\theta) = \begin{bmatrix} v_1 & 1 & 0 & \cdots & e^{i\theta} \\ 1 & v_2 & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ e^{-i\theta} & \cdot & \cdot & \cdots & v_p \end{bmatrix},$$

with $|v_1 - v_j| \leq 2\epsilon$ for all $j = 2, 3, \dots, p$. Thus $v_1 - v_j = r_j e^{i\theta_j}$ for some $r_j \leq 2\epsilon$ and $-\pi < \theta_j \leq \pi$. Then $f(\theta)$ can be written as

$$f(\theta) = \begin{bmatrix} v_1 & 1 & 0 & \cdots & e^{i\theta} \\ 1 & v_1 - r_2 e^{i\theta_2} & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ e^{-i\theta} & \cdot & \cdot & \cdots & v_1 - r_p e^{i\theta_p} \end{bmatrix}.$$

If we choose

$$f_1(\theta) = \begin{bmatrix} v_1 & 1 & 0 & \cdots & e^{i\theta} \\ 1 & v_1 & 1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ e^{-i\theta} & \cdot & \cdot & \cdots & v_1 \end{bmatrix},$$

then

$$f_1(\theta) - f(\theta) = \begin{bmatrix} 0 & 0 & 0 & \cdots & 0 \\ 0 & r_2 e^{i\theta_2} & 0 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ 0 & \cdot & \cdot & \cdots & r_p e^{i\theta_p} \end{bmatrix}$$

Thus we have $\|f_1(\theta) - f(\theta)\| \leq 2\epsilon$. By the discrete version of Borg's theorem proved in [5], the spectrum of the block Laurent operator A_1 corresponding to the matrix valued symbol $f_1(\cdot)$ is connected. Since $f(\theta)$ is Hermitian we have

$$\Lambda_{2\epsilon}(f(\theta)) = \sigma(f(\theta)) + \Delta_{2\epsilon}.$$

We also have

$$\Lambda_{2\epsilon}(A) = \bigcup_{-\pi < \theta \leq \pi} \Lambda_{2\epsilon}(f(\theta)) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f(\theta)) + \Delta_{2\epsilon}.$$

Let $A, A + E \in \mathbb{C}^{N \times N}$ be Hermitian matrices then $|\lambda_j(A) - \lambda_j(A + E)| \leq \|E\|$ where $\lambda_j(A)$ denotes the j^{th} eigenvalue of A , [6]. Therefore $|\lambda_j(f(\theta)) - \lambda_j(f_1(\theta))| \leq 2\epsilon$ for all $j = 1, 2, \dots, p$. This together with the connectedness of $\sigma(A_1) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f_1(\theta))$ implies that $\Lambda_\epsilon(A) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f(\theta)) + \Delta_{2\epsilon}$ is also connected. $\square$

Remark 2.3. The bound obtained in Theorem 2.1 involves the parameter p . This will create some computational obstacles when we deal with sequence of operators.

3. FURTHER GENERALIZATIONS

In the last section we have considered the one dimensional discrete Schrödinger operator with periodic potential and constant coefficients. In this section we will generalize the results to one dimensional discrete Schrödinger operator with periodic potential and variable coefficients. We also generalize the same results to a class of block Laurent operators.

3.1. Schrödinger operator with variable coefficient. Consider the one dimensional Schrödinger operator with periodic potential and variable coefficient defined by

$$\tilde{A}(u) = -\frac{d}{dx} \left(a \cdot \frac{d}{dx} u \right) + v \cdot u,$$

with a being positive and periodic with the same period as v . As similar to one dimensional Schrödinger operator with constant coefficient the finite difference approximation will lead $\tilde{A}$ to a general Jacobi operator (after some suitable scaling and translation). This can be represented as a bi-infinite symmetric matrix in the following form.

$$(3.1) \quad A_{n,\alpha}(p) = \begin{bmatrix} \ddots & & & & & & & & \\ & \ddots & & & & & & & \\ & & \ddots & & & & & & \\ & & & -\alpha_{p-1} & \gamma_0 & -\alpha_0 & & & \\ & & & & \ddots & & & & \\ & & & & & -\alpha_{p-2} & \gamma_{p-1} & -\alpha_{p-1} & \\ & & & & & & -\alpha_{p-1} & \gamma_0 & -\alpha_0 \\ & & & & & & & \ddots & \ddots & \ddots \\ & & & & & & & & \ddots & \ddots & \ddots \end{bmatrix},$$

with $\gamma_s = \alpha_s + \alpha_{(s+1) \bmod p} + h^2 v(x_{s;(j)})$ and $\alpha_s = a(x_{s+1/2, j})$, $x_{s+1/2, j} = j + h(p)(s + 1/2)$. Observe that resulting structure, up to the sign, represents the case of general p -periodic Jacobi matrices. As earlier, this can be identified as the block Laurent operator defined by

$$A := \begin{bmatrix} \cdot & \cdot & \cdot & \cdot & \cdots & \cdot & \cdot \\ \cdot & A_1 & A_0 & A_{-1} & \cdots & \cdot & \cdot \\ \cdot & \cdot & A_1 & A_0 & A_{-1} & \cdot & \cdot \\ \cdot & \cdot & \cdot & A_1 & A_0 & A_{-1} & \cdot \\ \cdot & \cdot & \cdots & \cdots & \cdot & \cdot & \cdot \end{bmatrix}$$

where each A_0, A_1, A_{-1} are $p \times p$ matrices defined respectively by

$$A_0 = \begin{bmatrix} v_1 & a_1 & 0 & \cdots & 0 \\ a_1 & v_2 & a_2 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdots \\ \cdot & \cdot & \cdot & \cdots & a_{p-1} \\ 0 & 0 & 0 & a_{p-1} & v_p \end{bmatrix}, \quad A_1 = \begin{bmatrix} 0 & 0 & \cdots & a_p \\ 0 & 0 & \cdots & 0 \\ \cdot & \cdot & \cdots & \cdot \\ 0 & 0 & \cdots & 0 \end{bmatrix}, \quad A_{-1} = \begin{bmatrix} 0 & 0 & \cdots & 0 \\ 0 & 0 & \cdots & 0 \\ \cdot & \cdot & \cdots & \cdot \\ a_p & 0 & \cdots & 0 \end{bmatrix}.$$

Notice that this infinite matrix gives the matrix representation of the bounded self-adjoint operator $A : \ell^2(\mathbb{Z}) \rightarrow \ell^2(\mathbb{Z})$ defined by

$$(3.2) \quad A(x_n) = (a_n x_{n-1} + a_n x_{n+1} + v_n x_n)$$

with respect to the standard orthonormal basis. The matrix valued symbol of A will have the following form for $-\pi < \theta \leq \pi$;

$$f(\theta) = \begin{bmatrix} v_1 & a_1 & 0 & \cdots & a_p e^{i\theta} \\ a_1 & v_2 & a_2 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ a_p e^{-i\theta} & \cdot & \cdot & \cdots & v_p \end{bmatrix}.$$

Assume that $a_{j+p} = a_j > 0$ for each j . This condition makes $f(\theta)$ to a self-adjoint matrix and the identities in equation 1.4 are true for $\sigma(A)$ and $\Lambda_\epsilon(A)$ (see [10]).

Theorem 2.1 and 2.2 will have their natural generalizations to the Jacobi case. The proof techniques are almost the same. However we present it below for the sake of completion .

Theorem 3.1. *Let A be the discrete Schrödinger operator with variable coefficients defined by (3.2). If the ϵ -pseudospectrum $\Lambda_\epsilon(A)$ of A is connected for some $\epsilon > 0$, then there exists a constant c such that $\sup_{k \in \mathbb{N}} |v_k - c| \leq 2\epsilon(p-1)$.*

Proof. The proof is merely an imitation of the proof of Theorem 2.1. Here the matrix-valued symbols are

$$f_k(\theta) = \begin{bmatrix} v_{k+1} & a_{k+1} & 0 & \cdots & a_{k+p}e^{i\theta} \\ a_{k+1} & v_{k+2} & a_{k+2} & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ a_{k+p}e^{-i\theta} & \cdot & \cdot & \cdots & v_{k+p} \end{bmatrix}.$$

It suffices to consider the sub matrices

$$J_k := \begin{bmatrix} v_{k+1} & a_{k+1} & 0 & \cdots & 0 \\ a_{k+1} & v_{k+2} & a_{k+1} & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ 0 & 0 & 0 & \cdots & v_{k+p-1} \end{bmatrix}, \quad k = 0, 1, \dots, p-1,$$

and apply Cauchy interlacing theorem for the eigenvalues of J_k . Considering J_0 and J_{i-1} for $i = 2, 3 \dots p$, we get

$$|v_{i-1} - v_p| = \left| \sum_{j=1}^{p-1} v_j - \sum_{j=i}^{p-2+i} v_j \right| = |\text{Trace}(J_0) - \text{Trace}(J_i)| \leq 2\epsilon(p-1).$$

Hence the proof is completed. $\square$

Theorem 3.2. *Let A be the discrete Schrödinger operator with variable coefficients defined by (3.2). If there exist $c_1, c_2 \in \mathbb{R}$ such that $\sup_{n \in \mathbb{Z}} |v_n - c_1| \leq \epsilon$ and $\sup_{n \in \mathbb{Z}} |a_n - c_2| \leq \epsilon$ for some $\epsilon > 0$. Then $\Lambda_{2\epsilon}(A)$ is connected.*

Proof. We have for $\epsilon > 0$, $\Lambda_\epsilon(A) = \bigcup_{-\pi < \theta \leq \pi} \Lambda_\epsilon(f_1(\theta)) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f_1(\theta)) + \Delta_\epsilon$, where $f_1(\theta)$ is the same $p \times p$ self-adjoint matrix defined in Theorem 3.1. Define

$$f(\theta) = \begin{bmatrix} v_1 & a_1 & 0 & \cdots & a_1e^{i\theta} \\ a_1 & v_1 & a_1 & \cdots & 0 \\ \cdot & \cdot & \cdot & \cdots & \cdot \\ a_1e^{-i\theta} & \cdot & \cdot & \cdots & v_1 \end{bmatrix}.$$

Let A be the discrete Schrödinger operator corresponding to f . We have

$$|\lambda_j(f(\theta)) - \lambda_j(f_1(\theta))| \leq \|f(\theta) - f_1(\theta)\| \leq 2\epsilon.$$

where $\lambda_j(f(\theta))$ denotes the j^{th} eigenvalue of $f(\theta)$. Since $\sigma(A) = \bigcup_{-\pi < \theta \leq \pi} \sigma(f(\theta))$ is connected (see [5]), we have the desired result. $\square$

Remark 3.3. It should be noticed that Theorem 3.1 gives the pseudospectral version of the Proposition 4.3 of [5]. One important open question is to obtain the pseudospectral analogue of Theorem 4.4 of [5]. That is to show that if the ϵ -pseudospectrum of A is connected for some $\epsilon > 0$, then the periodic sequence a_j is almost a constant sequence.

3.2. General block Laurent operators. Now we consider a general class of block Laurent operators and prove the pseudospectral version of Borg-type theorem for the same class. The proof techniques are not much different, but we have to take care of the convergence issues of the matrix entries. Theorem 4.1 of [8] can be modified in the following way.

Theorem 3.4. *Let A be the bounded operator defined by the block Toeplitz-Laurent matrix*

$$A = \begin{bmatrix} \ddots & \ddots & & & & & & & & & \\ \ddots & A_0 & A_{-1} & A_{-2} & & \dots & A_{-N} & \dots & & & \\ & A_1 & A_0 & A_{-1} & A_{-2} & & \dots & A_{-N} & \dots & & \\ & A_2 & A_1 & A_0 & A_{-1} & A_{-2} & & \dots & A_{-N} & \dots & \\ & & A_2 & A_1 & A_0 & A_{-1} & A_{-2} & & \dots & A_{-N} & \\ \dots & A_N & \dots & A_2 & A_1 & A_0 & A_{-1} & A_{-2} & & & \\ & \dots & A_N & \dots & A_2 & A_1 & A_0 & A_{-1} & A_{-2} & & \\ & & \dots & A_N & \dots & A_2 & A_1 & A_0 & A_{-1} & A_{-2} & \\ & & & \dots & A_N & \dots & A_2 & A_1 & A_0 & \ddots & \\ & & & & & \dots & & & & \ddots & \ddots \end{bmatrix},$$

where

$$A_0 = \begin{bmatrix} v_1 & 1 & & & a_0 \\ & 1 & v_2 & 1 & \\ & & 1 & \ddots & \ddots \\ & & & \ddots & \ddots \\ a_0 & & & & 1 & v_p \end{bmatrix}, \quad A_k = \begin{bmatrix} & & & & a_k \end{bmatrix} = A_{-k}^T,$$

such that $v_1 \leq v_2 \leq \dots \leq v_p$ and $\sum_k |a_k| < \infty$. If the pseudospectrum, $\Lambda_\epsilon(A)$ of A is connected for some $\epsilon > 0$, then there exists a constant c such that $\sup_k |v_k - c| \leq 2\epsilon(p-1)$.

Proof. The matrix-valued symbol associated with the block Toeplitz-Laurent operator A is

$$\tilde{f}(\theta) = \begin{bmatrix} v_1 & 1 & & & f(\theta) \\ & 1 & v_2 & 1 & \\ & & 1 & \ddots & \ddots \\ & & & \ddots & \ddots \\ \bar{f}(\theta) & & & & 1 & v_p \end{bmatrix}.$$

where $f(\theta) = \sum_k a_k e^{ik\theta}$. As in the previous theorem, we consider the sub matrices

$$P_1 = \begin{bmatrix} v_1 & 1 & & & \\ & 1 & v_2 & 1 & \\ & & 1 & \ddots & \ddots \\ & & & \ddots & \ddots \\ & & & & 1 & v_{p-1} \end{bmatrix}, \quad P_2 = \begin{bmatrix} v_2 & 1 & & & \\ & 1 & v_3 & 1 & \\ & & 1 & \ddots & \ddots \\ & & & \ddots & \ddots \\ & & & & 1 & v_p \end{bmatrix}.$$

If any of their eigenvalues are different, say $\lambda_j(P_1) < \lambda_j(P_2)$, then by Cauchy Interlacing theorem, $\lambda_j(\tilde{f}(\theta)) \leq \lambda_j(P_1) < \lambda_j(P_2) \leq \lambda_{j+1}(\tilde{f}(\theta))$, for all θ . Now the pseudospectrum $\Lambda_\epsilon(A)$ of A is connected and therefore the supremum of $\lambda_j(\tilde{f}(\theta)) + \epsilon$ is greater than or equal to the infimum of $\lambda_{j+1}(\tilde{f}(\theta)) - \epsilon$. Therefore we have $\lambda_j(P_2) - \lambda_j(P_1) \leq 2\epsilon$. Hence we get $|\lambda_i(P_2) - \lambda_i(P_1)| \leq 2\epsilon$ for every $i = 1, 2, \dots, p-1$.

$$\text{Therefore, } |\text{trace}(P_1) - \text{trace}(P_2)| = |v_1 - v_p| \leq 2(p-1)\epsilon.$$

Also since $v_1 \leq v_2 \leq \dots \leq v_p$, we get the desired conclusion with $c = v_j$ for some j . $\square$

Remark 3.5. The converse of the above result need not be true. That means if there exist $c \in \mathbb{R}$ such that $\sup_{k \in \mathbb{Z}} |v_k - c| \leq \epsilon$, then $\Lambda_{2\epsilon}(A)$ need not be connected.

Remark 3.6. Notice that we can not remove the assumption that $v_1 \leq v_2 \leq \dots \leq v_p$, since here we do not have the freedom to choose different symbols.

4. APPLICATIONS OF THE MAIN RESULTS

Consider a discrete Schrödinger operator A with non-periodic potential. Further assume that there exists a sequence of periodic discrete Schrödinger operators A_n converges to A in norm. In this section we develop some important results connecting spectrum and the potential function of A using the information of the spectrum and pseudospectrum of A_n . The following two lemmas establish the connection between spectrum of A_n and A . These results are folklore and we present it here for the sake of completeness. $BL(\mathbb{H})$ denotes the algebra of all bounded linear operators on the Hilbert space $\mathbb{H}$.

Lemma 4.1. *Let $A_n \in BL(\mathbb{H})$ and $A_n \rightarrow A$ in $BL(\mathbb{H})$. Further for each $n \in \mathbb{N}$ let $\lambda_n \in \sigma(A_n)$ and $\lambda_n \rightarrow \lambda$ as $n \rightarrow \infty$. Then $\lambda \in \sigma(A)$.*

Proof. We have $\|A_n - \lambda_n I - (A - \lambda I)\| \leq \|A_n - A\| + |\lambda_n - \lambda| \rightarrow 0$ as $n \rightarrow \infty$. Therefore the sequence of singular operators $A_n - \lambda_n I$ converges to $A - \lambda I$. Since the singular elements in $BL(\mathbb{H})$ is a closed set we have $A - \lambda I$ is not invertible. Hence $\lambda \in \sigma(A)$. $\square$

The following Lemma shows that the converse is also true whenever we consider a sequence of self-adjoint operators on $BL(\mathbb{H})$.

Lemma 4.2. *Let $A_n \in BL(\mathbb{H})$ and $A_n \rightarrow A$ in $BL(\mathbb{H})$. Further assume that each A_n are self-adjoint. Then the spectrum of A_n converges to the spectrum of A almost everywhere. That is the set $\sigma(A) \setminus \{\lambda = \lim_{n \rightarrow \infty} \lambda_n; \lambda_n \in \sigma(A_n)\}$ has Lebesgue measure 0.*

Proof. Since $A_n^* = A_n$ for each $n \in \mathbb{N}$ we have $A_n = U_n^* M_{f_n} U$ for some unitary operator $U_n : \mathbb{H} \rightarrow L^2(X, dx)$ and some suitable f_n known as the representer of A_n (Spectral Theorem for Bounded self-adjoint operators; see [3]). Also since A_n converges to A , A is self-adjoint and it has a representer, say f . Also,

$$\|A_n - A\| = \|M_{f_n} - M_f\| = \|f_n - f\|_\infty.$$

It is also true that the spectrum of A_n and spectrum of A are the essential range of f_n and f respectively. Since f_n converges to f almost everywhere, we have the desired result. $\square$

Corollary 4.3. *Let $A_n \in BL(\mathbb{H})$ and $A_n \rightarrow A$ in $BL(\mathbb{H})$. Further assume that each A_n are self-adjoint. Then the Hausdorff distance $d_H(\sigma(A), \sigma(A_n))$ between the spectrum of A and the spectrum of A_n converges to 0 as n tends to infinity.*

As a consequence, we obtain the following result for the discrete Schrödinger operator with a non periodic potential. Consider the discrete Schrödinger operator $A : \ell^2(\mathbb{Z}) \rightarrow \ell^2(\mathbb{Z})$ defined by equation 1.3 where the bounded potential $(v_k)_{k \in \mathbb{Z}}$ need not be periodic.

Theorem 4.4. *Let A be the discrete Schrödinger operator with a non-periodic potential (v_k) defined by (??). Assume that there exists a sequence A_n of discrete Schrödinger operator with periodic potentials such that A_n converges to A in norm and each A_n is of period p_n (that is the periodicity of the potential sequence v_k^n of A_n). Further assume that $\max\{p_n : n \in \mathbb{N}\} \leq p$ for some $p > 1$. If $\Lambda_\epsilon(A)$ is connected for some $\epsilon > 0$, then there exists a constant c such that $\sup\{|v_k - c| : k \in \mathbb{Z}\} \leq 2\epsilon(p - 1)$.*

Proof. We have A_n, A are self-adjoint and A_n converges to A . Hence given $\delta > 0$ there exists $n_1 \in \mathbb{N}$ such that $d_H(\sigma(A), \sigma(A_n)) < \delta$ for all $n \geq n_1$. It is also true that there exists $n_2 \in \mathbb{N}$ such that

$$\|A_n - A\| = \sup\{|v_k^n - v_k| : k \in \mathbb{Z}\} < \delta \text{ for all } n \geq n_2.$$

Define $n_3 := \max\{n_1, n_2\}$ and $n_\delta := \max\{n_3, p_{n_3}\}$. Since $\Lambda_\epsilon(A) = \sigma(A) + \Delta_\epsilon$ is connected $\sigma(A_{n_\delta}) + \Delta_{\epsilon+\delta} = \Lambda_{\epsilon+\delta}(A_{n_\delta})$ becomes connected. By Theorem 2.1, there exists a constant c

such that

$$\sup\{|v_k^{n_\delta} - c| : k \in \mathbb{Z}\} \leq 2(\epsilon + \delta)(p_{n_\delta} - 1) \leq 2(\epsilon + \delta)(p - 1).$$

Then we have for every $k \in \mathbb{Z}$,

$$\begin{aligned} |v_k - c| &= |v_k - v_k^{n_\delta} + v_k^{n_\delta} - c| \\ &\leq |v_k - v_k^{n_\delta}| + |v_k^{n_\delta} - c| \\ &\leq \delta + 2(\epsilon + \delta)(p - 1). \end{aligned}$$

Since $\delta > 0$ was arbitrary, we have $|v_k - c| \leq 2\epsilon(p - 1)$. Hence the proof. $\square$

4.1. Ten Martini Problem. The well-known Ten Martini conjecture asserted by Barry Simon states the following; If we consider the almost periodic Mathieu potential say, $v_j = \cos(2\pi j\alpha)$, where α is an irrational number, then the spectrum of the associated discrete Schrödinger operator is a Cantor-like set. This conjecture was settled and many modified proofs are also available in the literature (see [1] and references there in for more details). One possible approach to this problem was mentioned in [9] using the approximation by sequence of periodic Schrödinger operators. We report some progress to this approach below as an application of Theorem 4.4.

Consider a sequence of rational numbers α_n converges to α . The operators A_n with potential $v_j^n = \cos(2\pi j\alpha_n)$ converge to the almost Mathieu operator A . Even though A is not periodic, each A_n is periodic and have spectral gaps for each n . If the size of spectral gaps of A_n decreases and the number of gaps increases as n increases, then we have large number of smaller spectral gaps for large n . The spectrum of A_n is obtained after removing these spectral gaps from the interval. As in the construction of Cantor set, after each stage we are removing more number of open intervals. Proceeding in this way, we expect a much simpler proof for Ten Martini conjecture.

The approximation by sequence of periodic Schrödinger operator is a crucial step in this approach. How to choose an appropriate sequence is a challenging issue and if we apply Theorem 4.4 to almost Mathieu operator, since the ϵ -pseudospectrum is connected for every $\epsilon > 0$, we arrive at the contradiction that the Mathieu potential is constant. Hence the hypothesis of Theorem 4.4 does not hold for almost Mathieu operator and therefore periods of the operator sequence that converges to the almost Mathieu operator is not bounded. However, we can choose the approximating sequence A_n with periodic potentials v_k^n in such

a way that the sequence of periods $p_n = \frac{a_n}{b_n}$ with b_n non decreasing. This can be proved without much difficulty. This is the first step in solving Ten Martini problem in the above mentioned way. We end this section by proving this.

Theorem 4.5. *Let A be the discrete Schrödinger operator with almost Mathieu potential $\cos(2\pi j\alpha)$; α irrational. Then there exists a sequence A_n of discrete Schrödinger operators with periodic potential v_j^n such that $\|A_n - A\| \rightarrow 0$ as $n \rightarrow \infty$ and the sequence p_n of periods of v_j^n is non decreasing.*

Proof. Consider a sequence α_n of rationals converges to α and let A_n be the discrete Schrödinger operator with potential $v_j^n = \cos(2\pi j\alpha_n)$. Then it is easy to verify that $\|A_n - A\| \rightarrow 0$ as $n \rightarrow \infty$. We will show that the sequence α_n can be chosen in such a way that sequence p_n of periods of v_j^n is non decreasing.

Claim I: If $\alpha_n = \frac{a_n}{b_n}$, then the minimal period of v_j^n is $b_n + 1$.

It is easy to verify that $b_n + 1$ is a period of v_j^n . For we have,

$$v_{b_n+1}^n = \cos(2\pi(b_n + 1)\frac{a_n}{b_n}) = \cos(2\pi a_n + 2\pi\frac{a_n}{b_n}) = \cos(2\pi\frac{a_n}{b_n}) = v_1^n.$$

To show that $b_n + 1$ is the minimal period, we list the sequence as $v_1^n, v_2^n, \dots, v_{b_n+1}^n = v_1^n$. If there exists some j with $2 \leq j < b_n + 1$, and $v_1^n = v_j^n$, then $\cos(2\pi\frac{a_n}{b_n}) = \cos(2\pi j\frac{a_n}{b_n})$. Therefore, $2\pi j\frac{a_n}{b_n} = 2\pi\frac{a_n}{b_n} + 2\pi k$, for some natural number k . Hence $j\frac{a_n}{b_n} = \frac{a_n}{b_n} + k$ and $(j - 1)\frac{a_n}{b_n} = k, j = 2, 3, \dots, b_n$. That means the set $\{\frac{a_n}{b_n}, 2\frac{a_n}{b_n}, \dots, (b_n - 1)\frac{a_n}{b_n}\}$ contains at least one natural number. This is not possible since a_n and b_n have no common factors.

Claim II: $\alpha_n = \frac{a_n}{b_n}$, can be chosen in such a way that $b_n \leq b_{n+1}$.

Consider $\{\frac{1}{b_1}, \frac{1}{b_2}, \dots\}$ then it is a bounded sequence and therefore it has a convergent subsequence say $(\frac{1}{b_n})$. Also, it has a monotonically decreasing subsequence which we denote by the same notation $(\frac{1}{b_n})$. Now we consider $(\frac{a_n}{b_n})$ and obtain the desired conclusion. $\square$

Remark 4.6. We remark that using the above results, we are able to approximate almost Mathieu operator by a sequence of discrete Schrödinger operators with non decreasing period. Once we are able to connect the number of spectral gaps with the periodicity (that means if the number of spectral gaps increases as the periodicity increases), then this may lead to a solution to Ten Martini problem mentioned above.



5. NUMERICAL ILLUSTRATIONS

In this section, we report the results of some numerical experiments done using matlab. There are many efficient algorithms to compute the pseudospectra of matrices. Since our aim is only to illustrate the above results, we do not make any claim about the efficiency of this algorithm.

Example 5.1. Consider the 5×5 matrix $f(\theta)$ defined by

$$f(\theta) = \begin{bmatrix} 1 & 1 & 0 & 0 & e^{i\theta} \\ 1 & 1.1 & 1 & 0 & 0 \\ 0 & 1 & 1.2 & 1 & 0 \\ 0 & 0 & 1 & 1.3 & 1 \\ e^{-i\theta} & 0 & 0 & 1 & 1.4 \end{bmatrix}.$$



It is true that $f(\theta)$ will be the symbol matrix corresponding to some discrete Schrödinger operator A (after some suitable scaling and translation). We have $v_1 = 1, v_2 = 1.1, v_3 = 1.2, v_4 = 1.3, v_5 = 1.4$ and $|v_i - 1.2| \leq 0.2$ for all $i = 1, \dots, 5$. Figure 1 is $\sigma(A)$ and Figure 2 is $\Lambda_{0.2}(A)$. We have $\sigma(A)$ is disconnected and $\Lambda_{0.2}(A)$ is connected.



Example 5.2. Consider the 10×10 matrix $f(\theta)$ defined by

$$f(\theta) = \begin{bmatrix} 0 & 1 & 0 & \dots & \dots & e^{i\theta} \\ 1 & 0.05 & 1 & 0 & \dots & 0 \\ 0 & 1 & 0.1 & 1 & \dots & 0 \\ \dots & \dots & \dots & \dots & \dots & \dots \\ e^{-i\theta} & 0 & 0 & 0 & \dots & 0.45 \end{bmatrix}_{10 \times 10}.$$

It is true that $f(\theta)$ will be the symbol matrix corresponding to some discrete Schrödinger operator A (after some suitable scaling and translation). We have $v_1 = 0, v_2 = 0.05, \dots, v_{10} = 0.45$ and $|v_i - 0.225| \leq 0.225$ for all $i = 1, \dots, 10$. Figure 3 is $\sigma(A)$ and Figure 4 is $\Lambda_{0.225}(A)$. We have $\sigma(A)$ is disconnected and $\Lambda_{0.225}(A)$ is connected.



6. CONCLUDING REMARKS

We conclude this article by pointing out some of the important aspects of the considered problem and listing out some possible future problems. The results proved in section 2 are the pseudo spectral analogue of the results in [5] and [8]. In section 3, we could achieve much general and stronger results. The major ingredients in the proofs are pure linear algebra and therefore the techniques are much simpler. The connection between the main results and the Ten Martini problem discussed in section 4 poses a major challenge; that is to obtain a much simpler proof of Ten Martini conjecture. Notice that this well-known operator theoretic question has been addressed by several mathematicians and most of the proofs involve deep number theoretic techniques as far as we know. The goal is to use the pure linear algebraic tools to prove this conjecture. Here is the list of some open problems associated with this task.

- Estimating the size of spectral gaps is a very important as well as challenging problem.
- If we can show that the number of spectral gaps increases as the periodicity increases, that will be a useful result. There is an affirmative example discussed in [5] where the number of gaps is $p - 1$.
- The continuous case has to be addressed with the tools developed here. The pseudospectral version of the classical Borg's theorem is an interesting problem for future research.

Acknowledgements. The authors wish to thank Prof. M.N.N. Namboodiri for useful discussions.

REFERENCES

1. A. Avila, S. Jitomirskaya, *The Ten Martini Problem*, Ann. of Math. (2) **170** (2009), no. 1, 303–342.
2. G. Borg, *Eine Umkehrung der Sturm–Liouvilleschen Eigenwertaufgabe Bestimmung der Differentialgleichung durch die Eigenwerte*. Acta Math. **78** (1946), 1–96.
3. E. B. Davies, *Linear Operators and their Spectra*, Cambridge University Press, UK, 2007.
4. H. Flaschka, *Discrete and periodic illustrations of some aspects of the inverse method. Dynamical systems, theory and applications* pp. 441–466. Lecture Notes in Phys., Vol. 38, Springer, Berlin, 1975.
5. L. Golinskii, K. Kumar, M. N. N. Namboodiri, S. Serra, Capizzano, *A note on a Discrete Version of Borg's Theorem via Toeplitz- Laurent Operators with Matrix-Valued Symbols*, Bollettino U. M. I. (9) **IV** (2013), 205–218.
6. Golub, Gene H.; Van Loan, Charles F. *Matrix computations*. Third edition. Johns Hopkins Studies in the Mathematical Sciences. Johns Hopkins University Press, Baltimore, MD, 1996.
7. Kac, Mark. *Can one hear the shape of a drum?* Amer. Math. Monthly **73** 1966 no. 4, part II 1–23.
8. K. Kumar, M.N.N. Namboodiri and S. Serra-Capizzano, *Perturbation of operators and approximation of spectrum*, Proc. Indian Acad. Sci. Math. Sci. **124** (2014), no. 2, 205–224.
9. V. B. Kiran Kumar, *Preconditioners in spectral approximation*, Ann. Funct. Anal. **7** (2016), no. 2, 326–337.
10. G. Krishna Kumar, Kulkarni, S. H. *Banach algebra techniques to compute spectra, pseudospectra and condition spectra of some block operators with continuous symbols*. Ann. Funct. Anal. **6** (2015), no. 1, 148–169.
11. Trefethen, Lloyd N.; Embree, Mark. *Spectra and pseudospectra. The behavior of nonnormal matrices and operators*. Princeton University Press, Princeton, NJ, 2005.

¹ COCHIN UNIVERSITY OF SCIENCE AND TECHNOLOGY, KERALA, INDIA.
E-mail address: kiranbalu36@gmail.com

² DEPARTMENT OF MATHEMATICS, BJM GOVT. COLLEGE, CHAVARA, KERALA, INDIA.
E-mail address: krishna.math@gmail.com